



Multi-zone amplifier matrix **6x120W with BLUETOOTH source, DAB+RADIO, FM TUNER, USB and SD CARD integrated** for MP3 audio files reading.

IR remote control supplied

Sources selection and independent volume on each zone.

Power supply AC110-230V & 24Vdc.

Consumption 900VA

4 mix. inputs+ sources+ priority emergency input+ multi-zone desk microphone+ zone control.

CH1: internal sources BLUETOOTH, DAB RADIO, FM TUNER, USB, SD CARD zone management by buttons.

CH2-3-4: mic COMBO 5-8mV 600Ω phantom power (selectable)/ line XLR 150-470mV 10KΩ (switchable).

CH5: input AUX RCA.

CH6 EMC: priority emergency input for service or evacuation messages.

6 Output RJ45 for zones control or multi-zone desk microphone via [Vivaldi Ulisse BS6*](#).

2x Monitor Output with volume control and button (front panel) for zone selection:

-JACK 6,3mm for headphone on front panel.

-RCA for active speaker on rear panel.

Mute function adjustable.

6 line out RCA: 0,775V (0dBV), one on each channel controlled by zone volume (6).

Output 100V and 4-16Ω.

Horn output (siren sign)

VIVALDI

Antenna 75Ω for reception DAB RADIO.
High/Low tones control
Chime (DIN-DON signal) adjustable on front panel
Dimensions 448x88x405 mm (WxHxD)
2U rack.
Weight 7,0 Kg
Black cabinet, orange screen painting
Metal cabinet
It needs [Vivaldi Ulisse PSK](#) for rack support.

*it supports up to 6 BS6 o CR1.

Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice

Images

Vivaldi Ulisse MS6120BT



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it
P.IVA e C.F. 02880360272