



25+25W RMS power stereo amplifier, with analog audio input and integrated Bluetooth source.

Supplied with standard or custom PIN (PIN code programmed at the factory: name max 30 characters, password max 4 numbers) to be communicated when ordering.

Mono/stereo function selectable from DIP switch.

Select volume control mode from DIP switch. Internal volume (trimmer) or external potentiometers (mono ##Vivaldi Giove TVM##, stereo [Vivaldi Giove TVS](#)).

The built-in bluetooth source takes priority over the signal coming from the input. Built-in audio detector sensitivity adjustment.

STATUS LED:

Blue: Bluetooth Active

Green: presence of music signal

Red: Ignition

BUTTONS: play, pause

TECHNICAL DATA:

1x Clamp Local audio input (stereo) and 24Vdc power supply.

1x speaker connection terminal 25W @ 4-8Ohm per channel (minimum impedance 4Ω/channel).

2x terminals connection external remote potentiometer.

1x SMA connector for external bluetooth antenna and(if installed not in the room, but in a technical room).

Input sensitivity control depending on the type of external source.

Power supply via [Vivaldi Giove AL3B](#) (not included).

Current 1,2A.

VIVALDI

Size (WxHxD) 54x90x63 mm (3 Modules).

Weight 0.10 Kg

Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice

 Images

Vivaldi Giove A25SBTC



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it

P.IVA e C.F. 02880360272